

Classical Analogue of Electromagnetically Induced Transparency with a Metal-Superconductor Hybrid Metamaterial

Cihan Kurter,¹ Philippe Tassin,^{2,3} Lei Zhang,² Thomas Koschny,² Alexander P. Zhuravel,⁴ Alexey V. Ustinov,⁵ Steven M. Anlage,¹ and Costas M. Soukoulis^{2,6}

¹*Center for Nanophysics and Advanced Materials, Department of Physics, University of Maryland, College Park, Maryland 20742-4111, USA*

²*Ames Laboratory—U.S. DOE and Department of Physics and Astronomy, Iowa State University, Ames, Iowa 50011, USA*

³*Applied Physics Research Group, Vrije Universiteit Brussel, Pleinlaan 2, B-1050 Brussel, Belgium*

⁴*B. Verkin Institute for Low Temperature Physics and Engineering, National Academy of Sciences of Ukraine, 61103 Kharkov, Ukraine*

⁵*Physikalisches Institut and DFG-Center for Functional Nanostructures (CFN), Karlsruhe Institute of Technology, D-76128 Karlsruhe, Germany*

⁶*Department of Material Science and Technology, and Institute of Electronic Structure and Lasers (IESL), FORTH, University of Crete, 71110 Heraklion, Crete, Greece*

(Received 27 March 2011; revised manuscript received 20 June 2011; published 18 July 2011)

Metamaterials are engineered materials composed of small electrical circuits producing novel interactions with electromagnetic waves. Recently, a new class of metamaterials has been created to mimic the behavior of media displaying electromagnetically induced transparency (EIT). Here we introduce a planar EIT metamaterial that creates a very large loss contrast between the dark and radiative resonators by employing a superconducting Nb film in the dark element and a normal-metal Au film in the radiative element. Below the critical temperature of Nb, the resistance contrast opens up a transparency window along with a large enhancement in group delay, enabling a significant slowdown of waves. We further demonstrate precise control of the EIT response through changes in the superfluid density. Such tunable metamaterials may be useful for telecommunication because of their large delay-bandwidth products.

DOI: 10.1103/PhysRevLett.107.043901

PACS numbers: 42.70.-a, 41.20.Jb, 42.50.Gy, 74.25.N-

Electromagnetically induced transparency (EIT) is a quantum mechanical effect observed in three-level atomic systems in which a beam of light can find its way through the medium with almost no absorption [1,2]. The typical configuration involves two atomic states which can be independently excited to the same final state, but have a forbidden transition between them. A probe beam tuned near one allowed transition will show a Lorentzian absorption profile. In the presence of a coherent pump beam exciting the other allowed transition, there can be interference that produces a narrow transparency window for the probe beam, with simultaneously strong dispersion resulting in a significant enhancement of the group delay and the possibility of slowdown or storage of light [3–6].

The characteristics of EIT can be reproduced by a classical resonator model based on two oscillating masses coupled by a spring [7]. One mass with dissipation factor γ_1 is acted upon by an external force, whereas the other mass with dissipation of γ_2 is not driven directly. If $\gamma_2 \ll \gamma_1$, a greatly minimized absorption and steep dispersion are visible at a particular driving frequency, due to a superposition of normal modes with almost zero displacement of the lossy oscillator.

Several groups have recently demonstrated classical analogues of EIT, mostly with electromagnetic metamaterials made of resonant artificial elements [8–11]. One approach is to create an array of rings with asymmetric

splits enabling the excitation of trapped-current modes [8]. Another study has utilized a continuous fish-scale pattern to excite those normally inaccessible modes [9]. Highly symmetrical geometries have also been proposed, e.g., an array of double ring resonators for which the response does not depend on the polarization [11] and two mirrored splitting resonators (SRRs) with a cut wire at the center achieving enhanced transmission without breaking the symmetry [12]. Apart from metamaterials showing EIT at microwave frequencies, plasmonic structures have been designed [13] to create similar characteristics at optical frequencies [14].

Earlier efforts to demonstrate classical EIT using normal-metal electromagnetic oscillators have suffered from insufficient loss contrast between the dark and radiative resonators. Here, we present a design with a resistance contrast that is several orders of magnitude larger than previously reported. The proposed artificial molecule (metamolecule) of our metal-superconductor hybrid metamaterial consists of a double planar SRR made of a superconducting Nb film symmetrically located around a normal-metal (Au) strip (see the Supplemental Material [15] for details of the design and fabrication). Use of Nb limits operation to the sub-THz band; using a high- T_c superconductor instead of Nb might allow scaling of our structure to THz frequencies. The Au strip is oriented along the electric field of the fundamental waveguide mode and is designed to have an electric dipole resonance

around $f = 10.6$ GHz; it is thus the radiative element in the metamolecule. Each of the two SRRs have in general an electric dipole resonance (currents in both arms flowing in the same direction) and a magnetic dipole resonance (currents in both arms flowing in opposite directions, i.e., current circling around the SRR) [16]. The position of the gaps in the SRRs has been chosen such that the electric field of the fundamental waveguide mode cannot excite their magnetic dipole resonance. In a free space experiment, the gaps would have been in the middle of the SRRs, but here they are shifted towards the center in order to account for the mode profile of the incident wave. In this way, the magnetic dipole mode of the SRRs can be used as the dark mode in our metamaterial.

Furthermore, the geometry has been optimized to increase the loss contrast between the radiative (strip) and dark (SRRs) resonators. First, the width of the strip is small to increase its resistance. Second, the mirror symmetry of the double SRR avoids magnetic dipole radiation of the dark element [12]. In order to enhance the loss contrast, we have made the SRRs from a Nb thin film. Below the T_c of Nb, the microwave surface resistance of the dark element will be very small (about $20 \mu\Omega$ at 10 GHz and 4 K) [17]. In contrast, the strip is made of a normal metal that retains significant surface resistance at low temperatures.

We have performed the microwave transmittance and reflectance measurements on this metamaterial by placing the metamolecule in a Nb X-band waveguide. We have cooled the system down below the T_c of Nb, and measured the scattering parameters. In the transmittance spectrum in Fig. 1(a), we observe a broadband dip with three narrow resonance-shaped features with increased transmittance. This is quite different from earlier works [8–12] where only one narrow transmission peak is observed. The reflectance data give sharp dips in each transparency window where the transmittance is enhanced. The underlying Lorentzian stop band [dashed curve in Fig. 1(b)] is due to the electric dipole interaction between the wire and the incident field. It can also be shown from a simple coupled-resonator model [7,10] that the resonance-shaped features emerge when a dark resonator is coupled very weakly to the radiative resonator and when the dark resonator is of sufficiently high quality. The question that remains to be addressed is why we find three of these features in our experiment.

Our simulations (see the Supplemental Material [15] for details) can reproduce the experimental transmittance spectrum to a high degree of similarity [Fig. 1(b)]. We find that there is only one EIT-like transmission window if the sample is positioned with perfect symmetry in the waveguide, and that the two additional EIT features appear as soon as this symmetry is slightly broken, i.e., by slightly tilting or shifting the metamolecule, or even by using a mesh that lacks the required symmetry. Such deviations from the ideal position will undoubtedly be present in the experiment. This suggests that there are two extra dark modes that are uncoupled to the wire if symmetrically




FIG. 1 (color online). Transmittance and reflectance spectra. The transmittance shows a broad stop band originating from the coupling of the electromagnetic waves to the electric dipole mode of the wire, and three narrower resonancelike features that are associated with dark modes of the SRRs. (a) Experimental data at $T = 2.6$ K. The FWHM bandwidth of the resonant features is 9, 10, and 1 MHz for the transmittance peaks and 2, 1, and 0.1 MHz for the reflectance features. (b) Simulation data when the metamolecule is horizontally displaced by 0.1 mm from the center of the waveguide. The dashed blue line is a simulation of the wire only. The labels *a-d* correspond to the current distributions in Fig. 2.

located, but having a nonvanishing coupling as soon as the symmetry is broken.

Further evidence for this hypothesis can be gained from the current distributions obtained from the simulations shown in Figs. 2(a)–2(d). In Fig. 2(a), displaying the current distribution at $f = 10.62$ GHz [the feature labeled *a* in Fig. 1(b)], there is a large current density in the wire only; this is the electric dipole resonance of the wire. At the EIT feature at $f = 10.30$ GHz [*b* in Fig. 1(b)], we see large currents in the SRRs and only a little current in the wire commensurate with a dark mode excitation [Fig. 2(b)]. The




FIG. 2 (color online). Current distributions in the wire and the split-ring resonators. (a) The electric dipole resonance of the wire. (b) The antisymmetric hybridization of the electric dipole resonance of the SRRs. (c) The symmetric hybridization of the magnetic dipole resonance of the SRRs. (d) The antisymmetric hybridization of the magnetic dipole resonance of the SRRs.

current distribution reveals that this dark mode is one of the hybridizations of the electric dipole resonances of the SRRs. We see that the currents in the two different SRRs flow in opposite directions. Therefore, if the metamolecule is perfectly at the center of the waveguide, there will be no coupling between the wire and this dark mode and, hence, no EIT effect. However, if the symmetry is slightly broken, the currents in the two SRRs are no longer exactly opposite and a small coupling may be achieved. The EIT feature at $f = 10.41$ GHz [*c* in Fig. 1(b)] has the main currents circling around the SRRs—one in a clockwise direction, the other in a counterclockwise direction [Fig. 2(c)]; this is the symmetric hybridization of the magnetic dipole resonances of the SRRs that was observed in earlier work [12]. At the frequencies inside the EIT feature at $f = 10.49$ GHz [*d* in Fig. 1(b)], the current density is again circling the SRRs, but now in the same direction for both SRRs [Fig. 2(d)]; this is the antisymmetric hybridization of the magnetic dipole resonances of the SRRs. It may again be inferred from symmetry considerations that this hybridization has vanishing coupling to the electric dipole mode of the strip only if the molecule is positioned exactly in the middle of the waveguide. These considerations explain the origin of the three EIT features; the resonance shape of the features is explained by constructive (destructive) interference of the current induced in the wire by the SRRs and the current directly excited by the external wave for the peak (dip) in transmittance.

We now proceed with our measurements of the group delay [Fig. 3(a)] [18], which are reproduced well by the simulations [Fig. 3(b)]. We observe significantly enhanced group delay inside the three EIT transmission windows, in particular, for the highest-frequency EIT feature for which we find a group delay above 300 ns. Indeed, the group delay enhancement is related to the linewidth of the EIT feature, which is in turn determined by the coupling strength [19]. Since the coupling of the highest-frequency dark mode is introduced by a slight misalignment, it can be




FIG. 3 (color online). The group delay of the metamaterial obtained (a) from the experiment at $T = 2.6$ K (b) from the numerical simulations.

made arbitrarily small, unlike the middle EIT feature for which the maximal group delay is limited by the overall size of the metamolecule. With the use of a superconductor, we can now achieve large group delays from a sub-wavelength thin metamolecule, which may find application as compact delay lines with phase shifts on the order 10^4 rad. The delay-bandwidth product (DBP) of our structure is 0.3, which approaches the DBPs in resonant cavities ($\text{DBP} \approx 1$), but is still smaller than media containing atomic vapors ($\text{DBP} \approx 10$) and some photonic crystal waveguides that can achieve a DBP over 100, but we should keep in mind that the latter systems are much longer than a single wavelength [20].

The reader should also note the transmittance contrast of about 40 dB between the peaks of the EIT windows and the transmittance dip associated with the wire response. This has to be compared with less than 10 dB for normal-metal EIT metamaterials with similar geometry [12], i.e., a difference of 3 orders of magnitude. The significantly improved transmittance contrast is the direct consequence of the reduced loss in the dark element by employing a superconductor. The presence of the superconductor is critical in this experiment because the weakly coupled EIT resonances with large group delay are very sensitive to loss and would be destroyed if a superconductor were not used.

We investigate now the temperature dependence of the metamaterial response. We have plotted the measured transmittance [Fig. 4(a)] and group delay [Fig. 4(b)] for a




FIG. 4 (color online). Temperature dependence of the measured (a) transmittance and (b) group delay of the metamaterial. The pronounced EIT features and the enhanced group delay at the lowest temperature vanish if the temperature is increased above the critical temperature of Nb. The inset in (a) shows the frequency of the rightmost EIT feature as a function of temperature. The inset in (b) shows the peak group delay at the rightmost EIT feature as a function of temperature. The incident power was -20 dBm.

set of temperatures. The enhancement of the transmittance and the group delay [inset of Fig. 4(b)] both decrease with increasing temperature. This is due to the increase in Ohmic loss of the superconductor, originating from a larger fraction of electrons in the normal state, which at high temperatures finally leads to an insufficient loss contrast to support classical EIT. We also observe that the frequency of the EIT features shifts downward with increasing temperature [inset of Fig. 4(a)], which is mainly due to the increase in kinetic inductance of Nb as the superfluid density decreases [21,22]. The EIT feature also broadens with increasing temperature due to the increase in losses. The EIT effect finally disappears at the critical temperature as Nb enters the normal state and its Ohmic losses exceed those of the Au radiative resonator. The magnetic field required for tuning in this structure is estimated to be on the order of 1 A/m. The switching time will likely be limited by the time it takes to drive the superconducting resonators into the normal state. We estimate this to be on the order of microseconds for microwave magnetic fields. Other methods to tune metamaterials at these frequencies include varactor diodes, microelectromechanical system switches, photocarrier generation, or mechanical tuning, all of which involve additional losses, and none of them will be significantly faster than our method.

In summary, we have created a planar metal-superconductor hybrid metamolecule that displays classical EIT with far greater loss contrast, transmittance, and group delay than ever before demonstrated. Under these circumstances, two new dark modes become visible, and they can be designed to create multiple strong EIT windows. By manipulation of the superconducting properties of the dark resonators through temperature or magnetic field, the EIT effects are tunable to an unprecedented extent.

The work at Maryland was supported by ONR Contracts No. N000140811058 and No. 20101144225000, the U.S. DOE (High Energy Physics) under Contract No. DESC0004950, the ONR/UMD AppEl Center, task D10 (Contract No. N000140911190), and CNAM. The work at Ames Lab was partially supported by the U.S. DOE (Basic Energy Science) under Contract No. DE-AC02-07CH11358 (computational studies), by ONR Contract No. N000141010925 (characterization), and by the EU FET project PHOME, Contract No. 213310 (theory). The work in Karlsruhe is supported by the DFG Center for Functional Nanostructures, the German International Bureau of the Federal Ministry of Education and Research (BMBF) under Grant No. UKR08/011, a NASU program on “nanostructures, materials and technologies,” and the Fundamental Researches State Fund of Ukraine. P.T. acknowledges support from the Belgian American Educational Foundation.

- [1] A.B. Matsko, O. Kocharovskaya, Y. Rostovtsev, G.R. Welch, A.S. Zibrov, and M.O. Scully, *Adv. At. Mol. Opt. Phys.* **46**, 191 (2001).
- [2] M. Fleischhauer, A. Imamoglu, and J.P. Marangos, *Rev. Mod. Phys.* **77**, 633 (2005).
- [3] L.V. Hau, S.E. Harris, Z. Dutton, and C.H. Behroozi, *Nature (London)* **397**, 594 (1999).
- [4] M. Fleischhauer and M.D. Lukin, *Phys. Rev. Lett.* **84**, 5094 (2000).
- [5] C. Liu, Z. Dutton, C.H. Behroozi, and L.V. Hau, *Nature (London)* **409**, 490 (2001).
- [6] M. Bajcsy, A.S. Zibrov, and M.D. Lukin, *Nature (London)* **426**, 638 (2003).
- [7] C.L. Garrido Alzar, M.A.G. Martinez, and P. Nussensveig, *Am. J. Phys.* **70**, 37 (2002).
- [8] V.A. Fedotov, M. Rose, S.L. Prosvirnin, N. Papasimakis, and N.I. Zheludev, *Phys. Rev. Lett.* **99**, 147401 (2007).
- [9] N. Papasimakis, V.A. Fedotov, N.I. Zheludev, and S.L. Prosvirnin, *Phys. Rev. Lett.* **101**, 253903 (2008).
- [10] P. Tassin, L. Zhang, T. Koschny, E.N. Economou, and C.M. Soukoulis, *Phys. Rev. Lett.* **102**, 053901 (2009).
- [11] N. Papasimakis, Y.H. Fu, V.A. Fedotov, S.L. Prosvirnin, D.P. Tsai, and N.I. Zheludev, *Appl. Phys. Lett.* **94**, 211902 (2009).
- [12] L. Zhang, P. Tassin, T. Koschny, C. Kurter, S.M. Anlage, and C.M. Soukoulis, *Appl. Phys. Lett.* **97**, 241904 (2010).
- [13] S. Zhang, D.A. Genov, Y. Wang, M. Liu, and X. Zhang, *Phys. Rev. Lett.* **101**, 047401 (2008).
- [14] N. Liu, T. Weiss, M. Mesch, L. Langguth, U. Eigenthaler, M. Hirscher, C. Sonnichsen, and H. Giessen, *Nano Lett.* **10**, 1103 (2010).
- [15] See Supplemental Material at <http://link.aps.org/supplemental/10.1103/PhysRevLett.107.043901> for details of design, fabrication, simulation, and measurement of the metal-superconductor hybrid metamaterial.
- [16] The frequencies of the EIT resonances, i.e., of the dark modes can be positioned below or above the radiative resonance by proper design of the SRRs.
- [17] M.S. Pambianchi, S.M. Anlage, E.S. Hellman, J.E.H. Hartford, M. Bruns, and S.Y. Lee, *Appl. Phys. Lett.* **64**, 244 (1994); M.S. Pambianchi, L. Chen, and S.M. Anlage, *Phys. Rev. B* **54**, 3508 (1996).
- [18] The offset in the measured group delay is caused by the delay of the waves in the transmission lines (coaxial cables + waveguide) used in our measurements. We estimate this delay to be 26 ns, consistent with the measured background delay.
- [19] P. Tassin, L. Zhang, T. Koschny, E.N. Economou, and C.M. Soukoulis, *Opt. Express* **17**, 5595 (2009).
- [20] T. Baba, J. Adachi, N. Ishikura, Y. Hamachi, H. Sasaki, T. Kawasaki, and D. Mori, *Proc. Jpn. Acad. Ser. B* **85**, 443 (2009).
- [21] M.C. Ricci and S.M. Anlage, *Appl. Phys. Lett.* **88**, 264102 (2006).
- [22] H.-T. Chen, H. Yang, R. Singh, J.F. O'Hara, A.K. Azad, S.A. Trugman, Q.X. Jia, and A.J. Taylor, *Phys. Rev. Lett.* **105**, 247402 (2010).